

# Transmit Combiner

## CMB8I Transmit Combiner

8 Inputs x 1 Output Transmit Power Combiner  
10 Watts  
8 Tuned isolator inputs 30MHz BW  
Insertion loss -10dbm.  
Port to Port Isolation 60dbm @ 470-600MHz  
Designed to be used in ADP401 and SPI8 in distribution applications



## SPECIFICATIONS

RF Carrier Frequency Range: 10Mhz -1Ghz  
Maximum RF Input No Damage: 10 watts  
Insertion Gain/Loss: -9dbm  
Impedance: 50 Ohms  
Net Weight: 8 lbs  
Overall Dimensions: 19 x 11.5 x 1.75 inches  
Input/Output Connector Type: BNC Female

